

# (2+1)×1 Multi-Mode Pump Combiner (MPC)

## Description


This  $(2+1)\times 1$  multi-mode fiber combiner is designed for high power fiber laser application. It combines two pump lasers and one signal channel into one double cladding output fiber. Fiber type can be customized.

### **Key Features**

- High Signal Transfer Efficiency
- High Pump Efficiency
- Wavelength Insensitive
- Custom Configurations Available


## Mechanical Dimension

### C4: 70x12x8





## C7: 100x15x10





#### Unit: mm



## **Specifications**

Parameters/Test conditions			Min	Typ.	Max	Unit	Note
1	Signal Operating Wavelength		1000	1064	1100	nm	
2	Pump Operating Wavelength		800		1000	nm	
3	Pump Fiber	Core Diameter		200		μm	Refer to fiber codes
4		Cladding Diameter		220		μm	
5		Numerical Aperture		0.22	-		
6	6 Signal Fiber		20/400 SCF or 20/400 DC			CF	Refer to fiber codes
			Pump Efficiency		Signal Insertion		
			(%) Los		Loss (	dB)	Refer to fiber codes
7	Output	20/400 DCF	>90 (Typ. 93)		<0.5 (Typ. 0.3)		Refer to fiber codes
	Fiber	20/400 Der					
8	M <sup>2</sup>				1.3	-	
9	Optical Isolation		25	30		dB	
10	Fiber Length		0.8			m	Each port
11	Power Handling			50	100	W	Each port
12	Operating Environment Temperature		-5		+70	°C	
13	Operating Humidity		5		95	%RH	Not recommend in high
15							humidity for long time.
14	Storage Temperature		-40		+85	°C	
15	Package		C4, C7			-	Handling power is
15							different with PKG

## Ordering Information

MPC-(2+1)×1-F(B)-Pump wavelength/Pump power-Signal wavelength-Pump fiber/Signal fiber-Output fiber-Package-Fiber length

### Note :

F: Forward pump; B: Backward pump.Pump/Signal/Output fiber: refer to fiber codes.Package: C4, C7C4: 25W/port; C7: 100W/port